

INPUT PROCESSING METHOD AND INPUT CONTROL APPARATUS

BACKGROUND OF THE INVENTION

5 1. Field of the Invention

The present invention relates to a method for processing input from a touch input device such as a tablet or the like used as an input device, and an input control apparatus for implementing the method.

10 2. Description of the Related Art

Portable information processing apparatuses, which are becoming popular, utilize touch input devices such as tablets or digitizers as input devices instead of mice. Generally, a tablet or digitizer is integrated with a display such as a liquid crystal display by being mounted as a transparent plate over the display or placed underneath the display, and is configured to detect the position of a stylus pen or the like on the display when the stylus pen or the like, as a pointing device, contacts the display screen.

Such input devices, generally called touch screens or touch panels, have been implemented in various ways, including one that uses a resistive film (pressure sensitive tablet) consisting of transparent electrodes bonded to the surface of a display (CRT, LCD, plasma display, etc.) and performs an input operation by touching the screen with a finger or a pen, and one that performs an input operation on the screen with the digitizer, mounted underneath the display, detecting the position of the input by detecting the magnetism being generated at the tip of the pen (when the pen is touched to the screen, magnetism is generated, and the position of the input is detected by the electromagnetic induction type digitizer mounted underneath the display). In addition to such pressure sensitive tablet and electromagnetic induction digitizer methods, various methods of input position detection have been

implemented, such as an ultrasonic surface acoustic wave touch panel method that uses ultrasonic waves.

5 A tablet, like a mouse, is also used to specify a position in a graphical input operation, select a menu or activate a software program by manipulating an icon, and so on.

10 A mouse contains mouse buttons, and a mouse operation to press and release a mouse button is called a mouse click, the mouse operation being classified as a single click, double click, etc. according to how many times the button is pressed in succession. By putting the mouse cursor on a designated icon and clicking the mouse on it, desired processing can be specified. In the case of a pen operation on a tablet, if an operation to touch the pen or the like to the tablet (called a pen down motion) and then lift it off the tablet (called a pen up motion) is called a tap, then moving the mouse cursor and single-clicking or double-clicking the mouse corresponds to performing a single tap or double tap on a designated icon. The pen down and pen up motions here embrace operations performed not only by a pen but also by a finger or the like.

20 In a graphical input operation, when a tablet 10 is touched with a pen 14, as shown in Figure 1, a dot is drawn on a display 12 at the position of the touch. The figure shows the tablet 10 and display 12 as a single integral unit. When the pen 14 is moved by holding it touched to the tablet 10, a line corresponding to its movement is drawn on the display 12.

30 In the case of a mouse, there is a mouse operation, called drag, in which the mouse is moved while keeping the mouse button pressed down; in a graphical input operation, a line is drawn when the mouse is dragged. On the other hand, when the mouse is moved without holding down a mouse button, the mouse cursor merely moves on the display.

In the case of a graphical input operation by a

pen on a tablet, on the other hand, if a dot or line were always drawn with a pen down motion, an operation to move the cursor without drawing a dot or line, such as the operation shown in Figure 3, could not be accomplished.

5 To avoid this, an operation mode is provided in which even when the pen is actually touched to the tablet, the motion is not interpreted as a pen down motion but the mouse cursor is merely caused to move. This mode is called a hovering mode. To switch the operation between
10 normal mode and hovering mode, a normal mode selection button 16 and a hovering mode selection button 18 are provided outside the display screen, as shown in Figure 4. In an icon manipulation in the hovering mode, a pen tap on an icon only results in positioning the cursor on
15 that icon.

In this way, an input operation on a touch input device such as a tablet or digitizer has required mode switching using the buttons provided outside the screen, and in the case of an input operation that
20 requires frequent mode switching, the operation has been very tiring and inefficient for an operator.

SUMMARY OF THE INVENTION

The present invention has been devised in view of the above problem, and an object of the invention is to
25 provide an input processing method and input control apparatus for a touch input device that enables operation mode switching to be accomplished with a very simple operation.

To achieve the above object, according to the
30 present invention, there is provided an input processing method for a device which provides input by performing a touch motion on an operating surface, comprising: a first step of detecting the length of time of a non-touch state in which no touch motion is performed on the operating
35 surface; and a second step of determining information indicating a touch state in accordance with the detected length of time when a touch motion has occurred.

According to the present invention, there is also provided an input processing method for a device which provides input by performing a touch motion on an operating surface, comprising: a first step of detecting
5 the number of successive occurrences of the touch motion; and a second step of determining information indicating a touch state in accordance with the detected number of occurrences.

According to the present invention, there is also provided an input processing method for a device which provides input by performing a touch motion on an operating surface, comprising: a first step of detecting
10 the number of occurrences of the touch motion over a predetermined length of time; and a second step of
15 determining information indicating a touch state in accordance with the detected number of occurrences.

According to the present invention, there is also provided an input processing method for a device which provides input by performing a touch motion on an
20 operating surface, comprising the steps of: detecting the number of successive occurrences of the touch motion; and determining a corresponding mouse operation in accordance with the detected number of occurrences.

Furthermore, according to the present invention,
25 there are provided an input control apparatus for implementing the above method, and a program recording medium which is readable by a computer utilizing the input control apparatus, and on which is recorded a program for implementing the above method.

30 BRIEF DESCRIPTION OF THE DRAWINGS

Further features and advantages of the present invention will be apparent from the following description with reference to the accompanying drawings, in which:

Figure 1 is a diagram for explaining the motion for
35 drawing a dot with a pen;

Figure 2 is a diagram for explaining the motion for drawing a line with a pen;

Figure 3 is a diagram for explaining the motion for merely moving cursor coordinates without drawing a line;

Figure 4 is a diagram for explaining mode switching buttons according to the prior art;

5 Figure 5 is a perspective view of a portable information processing apparatus to which the present invention is applied;

10 Figures 6A and 6B are diagrams for explaining a pressure sensitive tablet and an electromagnetic induction tablet, respectively, as representative examples of tablets;

Figure 7 is a diagram showing the details of a hot pad;

15 Figure 8 is a block diagram showing the system configuration of the portable information processing apparatus shown in Figure 5;

Figure 9 is a flowchart illustrating the sequence of processing performed by a tablet controller;

20 Figure 10 is a diagram showing the format of data sent out from the tablet controller;

Figure 11 is a diagram for explaining the operation of the tablet controller;

Figure 12 is a flowchart illustrating a pen driver processing sequence;

25 Figure 13 is a diagram for explaining the operation of the pen driver;

Figure 14 is a flowchart illustrating a processing sequence of an OS during graphical input processing;

30 Figures 15A, 15B, and 15C are diagrams for explaining a method of operation mode switching according to the present invention;

Figures 16A, 16B, 16C, and 16D are diagrams for explaining a method of operation mode switching according to the prior art;

35 Figure 17 is a diagram for explaining pen motion and operation modes according to the present invention;

Figure 18 is a diagram for explaining pen motion and

operation modes according to the prior art;

Figure 19 is a diagram showing an example of an icon manipulation screen; and

Figures 20A and 20B are flowcharts illustrating a processing sequence of an OS during an icon manipulation.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

An embodiment of the present invention will be described below with reference to the accompanying drawings. The embodiment hereinafter described deals with an example that uses a pen (or stylus), but the invention is also applicable to devices that are operated using fingers. For example, ultrasonic surface acoustic wave touch panels and pressure sensitive tablets permit position input by touching them with a finger without using a pen. The present invention does not exclude application to such devices.

Figure 5 is a perspective view of a portable information processing apparatus to which the present invention is applied. A tablet 10 and a liquid crystal display 12 are combined together with one overlaid on top of the other, and function as electronic "paper". Various types of tablet 10 are commercially implemented, and the present invention is applicable to any type of tablet.

Figures 6A and 6B are diagrams for explaining a pressure sensitive tablet and an electromagnetic induction tablet, respectively, as representative examples of tablets. The pressure sensitive tablet 10 of Figure 6A consists of a transparent film and glass, and is mounted over the liquid crystal display 12. When the film is brought into contact with the glass by being pressed with a pen or the like, there occurs a change in the resistance value, based on which the position where the contact is made is detected. The electromagnetic induction tablet 10 of Figure 6B is constructed from a sensor plate containing a sensor coil, and is placed underneath the liquid crystal display 12. Pen position

is determined by detecting the magnetism, generated from the tip of the pen, by means of the sensor coil.

The details of a hot pad 20 in Figure 5 are illustrated in Figure 7. A hovering icon 22 on the hot pad 20 is an icon used for switching operation between the normal mode and an improved hovering mode according to the present invention. When the hovering icon 22 is touched during operation in the normal mode, the tablet 10 and display 12 operate in the improved hovering mode according to the present invention until this icon is touched again.

Figure 8 is a block diagram showing the system configuration of the portable information processing apparatus (the so-called pen computer) shown in Figure 5. A multichip module (MCM) 32, south bridge 38, and video graphics array (VGA) controller 36 are connected to a PCI (Peripheral Component Interconnect) bus 30. The south bridge 38, tablet controller 52, and ROM (read-only memory) 54 are connected to an ISA (Industry Standard Architecture) bus 50.

The multichip module 32 contains multiple bare silicon chips mounted on a small printed board, and comprises a CPU, a north bridge, and a secondary cache memory. The north bridge is a PCI system controller for controlling data transfers between the CPU, main memory, secondary cache memory, PCI bus, etc. A synchronous DRAM (SDRAM) 34 as the main memory is connected to the multichip module 32 via a memory bus. The SDRAM 34 is characterized by its operation synchronized to the system bus clock.

The VGA controller 36 controls the liquid crystal display 12 under the VGA standard. The south bridge 38 is a bridge, mounted with the PCI bus, that provides connections between the PCI bus and ISA bus on the motherboard, and controls data transfers between the CPU, memory, input/output devices, etc. A hard disk drive (HDD) 40 as an auxiliary storage device is connected to

the south bridge 38.

5 The tablet controller 52 is responsible for
controlling the processing of input from the tablet 10
and detecting an operation performed on the hot pad 20,
and includes a CPU 52a, a memory (RAM) 52b, and an
interface circuit 52c. The ROM 54 holds therein an
initial program loader.

10 A port replicator 60, also called an expansion I/O
box, connector box, expansion unit, or the like, is an
adaptor which is connected to a notebook computer or a
pen computer to enhance their expandability. Usually, it
accommodates various connectors, such as a serial port
60d, a parallel port 60a, and a CRT connector 60f, as
well as connection ports for a keyboard 60b, a mouse 60c,
15 a floppy disk drive 60e, an Ethernet port, etc.
Connectors that are infrequently used when the notebook
computer or pen computer is taken on the road are
accommodated in the port replicator.

20 In the present embodiment, the floppy disk drive 60e
is connected via the port replicator 60, but the floppy
disk drive may be connected directly to the pen computer,
or alternatively, the pen computer itself may be
constructed to contain a floppy disk. Further, the
floppy disk drive may be incorporated in a docking
25 station, rather than being connected via the port
replicator. A docking station is a device that contains
a SCSI card, an Ethernet card, a CD-ROM drive, a floppy
disk drive, an additional PC card expansion bus, etc.,
and mostly is shaped so that a notebook computer can fit
30 into it.

Programs may be provided using the CD-ROM drive or
the floppy disk drive accommodated in the docking
station.

35 Figure 9 is a flowchart illustrating the sequence of
processing that the CPU 52a within the tablet controller
52 performs in accordance with the program loaded into
the memory 52b of the controller 52. This program is

usually stored on the HDD 40, and is loaded into the memory of the tablet controller 52 at system power-up. The program may also be provided on other recording media such as a floppy disk or a CD-ROM. The illustrated
5 process is invoked as an interrupt service routine when a pen down motion is performed on the tablet 10.

First, in step 102, upon detecting the pen down motion, a pen down state flag and a pen down state start flag are both set to 1, and a pen down state end flag is
10 cleared to 0. The pen down state flag is a flag that is set to indicate that the current state is the pen down state, and the pen down state start flag is a flag that is set to 1 only once when a transition is made to the pen down state, while the pen down state end flag is a
15 flag that is set to indicate the end of the pen down state. These flags are implemented in the memory 52b within the tablet controller 52. Next, in step 104, it is determined whether the current operation mode is the improved hovering mode or not, based on the operation
20 performed on the hovering icon 22 on the hot pad 20. If the current mode is not the improved hovering mode, that is, if the current mode is the normal mode, the process proceeds to step 106; on the other hand, if the current mode is the improved hovering mode, the process proceeds
25 to step 108.

In step 106, an improved hovering mode flag, a flag that is set to indicate the improved hovering mode, is cleared to 0, i.e., set OFF. On the other hand, in step 108, the improved hovering mode flag is set to 1, i.e.,
30 ON. The improved hovering mode flag also is implemented in the memory 52b within the tablet controller 52. In step 110, which follows step 106 or 108, coordinate data indicating the position at which the tablet 10 is pressed by the pen is detected. In the case of a pressure
35 sensitive tablet, the coordinate data is detected by applying a voltage and measuring the resistance.

Next, in step 112, transmission data consisting of

status (1 byte) and coordinate data (4 bytes), as shown in Figure 10, is assembled in the memory 52b within the tablet controller 52, and is sent to the pen driver described later. The status byte contains a pen down state bit (pen down information), a pen down state start bit, a pen down state end bit, and an improved hovering mode bit, respectively indicating the values of the pen down state flag, pen down state start flag, pen down state end flag, and improved hovering mode flag.

10 In step 114, it is determined whether the current state is the pen up state, and if the state is not the pen up state, that is, if the state is still the pen down state, the process proceeds to step 116; on the other hand, if the state is the pen up state, the process
15 proceeds to step 118. In step 116, the pen down state start flag is cleared to 0, and the process loops back to step 110. In step 118, on the other hand, the pen down state flag and the pen down state start flag are both cleared to 0, while setting the pen down state end flag
20 to 1, and the status reflecting the contents of these flags is created and sent out. In this way, during the period from the pen down to the pen up, data is sent out at predetermined intervals of time (for example, every 5 ms).

25 The state transitions of the flags in the improved hovering mode in the above-described process will be described with reference to Figure 11. First, when the pen down motion is detected, the pen down state flag is set to 1, the pen down state start flag is set to 1, the
30 pen down state end flag is cleared to 0, and the improved hovering mode flag is set to 1 in steps 102, 104, and 108, as shown in case (A) in Figure 11. Then, these flag states are written in the status bits and sent out in step 112 together with the coordinate data detected in
35 step 110.

As long as the pen down state continues, the process consisting of steps 114, 116, 110, and 112 is carried out

in a loop fashion, as shown in case (B) in Figure 11; during that period, the pen down state flag remains at 1, the pen down state start flag remains at 0, and the pen down state end flag remains at 0. During the loop process, the coordinate data is constantly updated in step 110, and the coordinate data and the status are sent out in step 112 at predetermined intervals of time.

When a pen up motion is detected to end the pen down state, the process proceeds from step 114 to step 118, and the pen down state flag and pen down state start flag are now at 0 and the pen down state end flag is set to 1, as shown in case (C) in Figure 11. This forms the final status to be sent out. In the above process, if a pen up motion is detected immediately following the pen down motion, the flags make transitions from the states shown in case (A) in Figure 11 directly to the states shown in case (C) in Figure 11 without passing through the states shown in case (B) in Figure 11.

Figure 12 is a flowchart illustrating a pen driver processing sequence carried out by the CPU 32a within the multichip module 32. This pen driver program is usually stored on the HDD 40, and is loaded into the SDRAM 34 at system power-up and executed on the SDRAM 34. The program may be provided on other storage media such as a floppy disk or a CD-ROM. The illustrated process is initiated upon detecting the arrival of data sent from the tablet controller 52. First, in step 202, the data (see Figure 10) sent from the tablet controller 52 is received, and stored in a designated area within the SDRAM 34. Next, in step 204, the status in the received data is examined to determine whether the improved hovering mode bit is 1 or 0, and if the improved hovering mode bit is 1, the process proceeds to step 206; on the other hand, if the improved hovering mode bit is 0, the process proceeds to step 224.

In step 206, it is determined whether the pen down state end bit contained in the status byte in the

received data is 1 or 0, and if the pen down state end bit is 1, the process proceeds to step 208; on the other hand, if the pen down state end bit is 0, the process proceeds to step 210. In step 208, the countdown timer is set and started, whereupon the routine is terminated. This countdown timer is provided to measure the time interval between a pen up motion and a pen down motion, thereby to determine whether or not the length of time of the pen up state is less than a predetermined threshold value. This timer is implemented as a software timer in the SDRAM 34.

In step 210, it is determined whether the pen down state start bit contained in the status is 1 or 0, and if the pen down state start bit is 1, the process proceeds to step 212; on the other hand, if the pen down state start bit is 0, the process proceeds to step 220. In step 212, the countdown timer is checked to determine whether the timer has counted down 0 or not, and if the timer has not yet counted down to 0, that is, if the length of time of the pen up state is shorter than the predetermined length of time, the process proceeds to step 214; on the other hand, if the timer has already counted down to 0, that is, if the length of time of the pen up state is longer than the predetermined length of time, the process proceeds to step 218.

In step 214, hovering valid flag is set to 1, and the process proceeds to step 216. This hovering valid flag is a flag that is set to indicate that the hovering operation is to be performed validly in the improved hovering mode as it is originally intended. The flag is implemented in the SDRAM 34. In step 216, the pen down state bit in the status is changed to 0, and the process proceeds to step 224. On the other hand, in step 218, the hovering valid flag is cleared to 0 to invalidate the hovering operation in the improved hovering mode as an exception and thereby to effect the normal mode; then, the process proceeds to step 224.

In step 220, which is carried out when the pen down state start bit is detected as being 0 in step 210, the hovering valid flag is checked to determine whether it is at 1 or 0, and if the hovering valid flag is at 1, the process proceeds to step 222; on the other hand, if the hovering valid flag is at 0, the process proceeds to step 224. In step 222, the pen down state bit in the status is changed to 0, and the process proceeds to step 224. In the final step 224, the coordinate data and the status containing the pen down state bit after completion of the above processing are sent to the operating system (OS).

As the result of the above pen driver processing, the pen down state bit (pen down information) in the status reported to the OS along with the coordinate data is as follows. When the mode is not the improved hovering mode, that is, when the mode is the normal mode, steps 202, 204, and 224 are carried out in sequence, so that the pen down state bit remains unchanged at 1 and is reported as is.

Pen driver operation in the improved hovering mode, on the other hand, will be described below with reference to Figure 13. In the improved hovering mode, the operation differs depending on the time interval between the pen up motion and the pen down motion detected in the above process, that is, depending on whether or not the length of time of the pen up state is less than the threshold value set by the countdown timer.

First, since the pen down state end bit is 1 in the final status, that is, the status received when the pen down state has ended by detecting a pen up motion, the steps 202, 204, 206, and 208 are carried out, as shown in case (A) in Figure 13, and the countdown timer is thus set and started to count the time until the next pen down motion is detected.

Then, when the next pen down occurs with the countdown timer already reaching 0, that is, when a pen down motion is detected after the predetermined time has

elapsed from the preceding pen up motion, the first status received indicates that the pen down state bit is 1, the pen down state start bit is 1, and the pen down state end bit is 0, as shown in case (B) in Figure 13, and at this time, the countdown timer is already at 0; accordingly, the steps 202, 204, 206, 210, 212, 214, 216, and 224 are carried out in sequence. In the process, the hovering valid flag is set to 1 in step 214. The pen down state bit is changed to 0 in step 216, and the change state bit is reported to the OS in step 224. In other words, the number of pen down motions performed within the predetermined time is detected using the countdown timer, and if it is determined in step 212 that the countdown timer reads 0, that means that the number of pen down motions (touch motions) occurring in succession within the predetermined time is 1; as a result, the pen down state bit is not set ON, and it is determined that the state is not the pen down state.

In intermediate status received during the pen down state following the states shown in case (B) in Figure 13, the pen down state bit is 1, the pen down state start bit is 0, and the pen down end bit is 0, as shown in case (C) in Figure 13 and, at this time, the hovering valid flag is at 1; accordingly, the steps 202, 204, 206, 210, 220, 222, and 224 are carried out in sequence. Here again, the pen down state bit is changed to 0 in step 222, and the changed state bit is reported to the OS in step 224.

On the other hand, when the next pen down occurs with the countdown timer yet to reach 0, that is, when a pen down motion is detected before the predetermined time has elapsed from the preceding pen up motion, the first status received indicates that the pen down state bit is 1, the pen down state start bit is 1, and the pen down state end bit is 0, as shown in case (D) in Figure 13, and at this time, the countdown timer has not yet reached 0; accordingly, the steps 202, 204, 206, 210, 212, 218,

and 224 are carried out in sequence. In the process, the hovering valid flag is cleared to 0 in step 218. The pen down state bit remains unchanged at 1 and is reported to the OS as it is. In other words, the number of pen down motions performed within the predetermined time is detected using the countdown timer, and if it is determined in step 212 that the countdown timer has not yet reached 0, that means that the number of pen down motions (touch motions) occurring in succession within the predetermined time is 2 or more; as a result, the pen down state bit is set ON accordingly, and it is determined that the state is the pen down state.

In intermediate status received during the pen down state following the states shown in case (D) in Figure 13, the pen down state bit is 1, the pen down state start bit is 0, and the pen down state end bit is 0, as shown in case (E) in Figure 13, and at this time, the hovering valid flag is at 0; accordingly, the steps 202, 204, 206, 210, 220, and 224 are carried out in sequence. As a result, the pen down state bit remains unchanged at 1, and is reported to the OS as it is.

Following the states shown in case (B), (C), (D), or (E) in Figure 13, when the pen down states ends by detecting a pen up motion, and the final status is received, the countdown timer is started, as previously described, to prepare for the next pen down, as shown in case (A) in Figure 13.

Figure 14 is a flowchart illustrating the processing sequence of the OS during graphical input processing. This OS program is usually stored on the HDD 40, and is loaded into the SDRAM 34 at system power-up and executed on the SDRAM 34 by the CPU 32a within the multichip module 32. This OS program may be provided on other storage media such as a floppy disk or a CD-ROM. The illustrated process is initiated upon arrival of the data sent from the pen driver. First, in step 302, the data sent from the pen driver is received, and stored in a

designated area within the SDRAM 34. Next, in step 304, it is determined whether the pen down state bit in the status is 1 or 0, and if the pen down state bit is 1, the process proceeds to step 306; on the other hand, if the
5 pen down state bit is 0, the process proceeds to step 308.

In step 306, the cursor is moved while maintaining the pen down state which is equivalent to the state in which a mouse is clicked and held down. This causes a
10 dot or line to be drawn, just as if a mouse was dragged. On the other hand, in step 308, the cursor is merely moved to the position indicated by the received coordinate data.

According to the above-described tablet controller, pen driver, and OS processing operations, by just
15 performing an extra pen tap in the improved hovering mode, the immediately following pen tap works just like a pen tap performed in the normal mode. That is, supposing that the state shown in Figure 15A is a state in the
20 improved hovering mode, if a line drawing motion is performed on the tablet after performing a pen tap once, as shown in Figure 15B, a line is drawn on the display as in the normal mode, as shown in Figure 15C. After a series of drawing motions, a pen up state is entered, and
25 after the elapse of a certain amount of time, the hovering operation is again enabled. In the prior art, the pen had to be moved outside the screen to switch the mode, as shown in Figures 16A, 16B, 16C, and 16D, but according to the present invention, a smooth operation
30 becomes possible.

Pen motion and operation modes will be described in more detail when a line is drawn by temporarily entering the normal operation mode during the improved hovering mode and then resuming the hovering operation. In the
35 present invention, immediately before drawing a line, a pen tap is performed to switch the operation, and immediately after that, a line is drawn; when the pen is

lifted off the tablet after drawing the line, the hovering operation automatically resumes, as shown in Figure 17. In the prior art method, on the other hand, at timing A before drawing a line, the appropriate button
5 had to be pressed to switch to the normal mode, as shown in Figure 18, and then at timing B after drawing the line, another button had to be pressed to switch back to the hovering mode. The present invention eliminates the need for such troublesome button operations.

10 Next, a description will be given of icon manipulations in the improved hovering mode according to the present invention. Suppose an icon manipulation screen such as shown in Figure 19 is used in the improved hovering mode. In this case also, by just performing an
15 extra pen tap, the immediately following pen tap works just like a pen tap performed in the normal mode. More specifically, since the first tap is used for operation switching, the equivalent of a single click of a mouse is accomplished by a double tap of the pen, and the
20 equivalent of a double click of a mouse is accomplished by a triple tap of the pen.

Figures 20A and 20B are flowcharts illustrating the processing sequence of the OS during an icon
manipulation. This OS program is usually stored on the
25 HDD 40, and is loaded into the SDRAM 34 at system power-up and executed on the SDRAM 34 by the CPU 32a within the multichip module 32. This OS program may be provided on other storage media such as a floppy disk or a CD-ROM. The illustrated process is initiated upon arrival of the
30 data sent from the pen driver. As earlier described, for successively occurring pen taps, the pen driver sets the pen down state bit to 1 for the second and later taps, and sends this bit state to the OS. Accordingly, the OS interprets the second tap as the first mouse click.

35 First, in step 402, the data sent from the pen driver is received, and stored in a designated area within the SDRAM 34. Next, in step 404, it is determined

whether the pen down state bit and pen down state start bit in the status are both 1 or not, and if the result is YES, the process proceeds to step 406; on the other hand, if the result is NO, the routine is terminated.

5 In step 406, it is determined whether an interrupt timer value, which will be set in the following step 408, is 0 or not, and if the timer value is 0, the process proceeds to step 408; on the other hand, if the timer value is not 0, the process proceeds to step 410. In
10 step 408, the interrupt timer is set, and the routine is terminated. In step 410, on the other hand, it is decided that the next pen down has occurred within the predetermined time from the previous pen down, and the interrupt timer is reset. In the next step 412, it is
15 determined that a double click has occurred.

 When an interrupt is caused by the interrupt timer set in step 408, the process shown in Figure 20B is carried out. Since this process is invoked when the next pen down did not occur within the predetermined time from
20 the previous pen down, it is determined in step 450 that a single click has occurred.

 When a single click is detected, a file selection or other operation is performed, and when a double click is detected, a program in the file is activated, for
25 example.

 As described above, according to the present invention, in an information processing apparatus that uses a touch input device such as a tablet or digitizer instead of a mouse as an input device, switching between
30 normal operation and hovering operation can be accomplished with a very simple operation, enhancing its usability. Though the embodiment has been described by dealing with an example that uses a pen (or stylus), the present invention is also applicable to an apparatus that
35 is operated by a finger.

 The invention may be embodied in other specific forms without departing from the spirit or essential

characteristics thereof. The present embodiment is therefore to be considered in all respects as illustrative and not restrictive, the scope of the invention being indicated by the appended claims rather than by the foregoing description and all changes which come within the meaning and range of equivalency of the claims are therefore intended to be embraced therein.

5

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222